Fuzzy System Approximation based Adaptive Sliding Mode Control for Nonlinear System

Monisha Pathak, Mrinal Buragohain



Abstract: This paper introduces an adaptive sliding mode control that utilises a fuzzy system approximation. The fuzzy system is used to approximate the unknown function of an uncertain nonlinear system. The sliding mode control ensures the system's robustness, while the adaptive fuzzy system enhances real-time performance. To approximate unknown nonlinearities, a set of fuzzy rules is formulated whose parameters are adjusted in real-time by an adaptive algorithm. The chattering problem associated with sliding mode control is satisfactorily resolved, ensuring stable operation.

Keywords: Sliding Mode Control, Fuzzy Logic Control; Nonlinear system; Adaptive Control; Fuzzy System Approximation.

I. INTRODUCTION

Control theory, combined with fuzzy logic, has significantly expanded the use of controllers to manage complex, nonlinear systems. Fuzzy logic control (FLC) has several advantages over traditional techniques, such as the ability to include human experience, expert knowledge, a flexible model-free approach, and more [1]. Fuzzy controllers are intended to function in situations where there is a great deal of uncertainty or unknown variance in the characteristics and structures of the plants [6].

Adaptive fuzzy control techniques have advanced significantly since the fuzzy system universal approximation theorem [4, 9] was proposed. They are successfully applied in many different fields, such as system modelling, signal processing, pattern recognition, and system control [2, 3], etc. As a result, sophisticated controllers and complex plant representations have been created using intelligent control techniques [5, 10]. Maintaining consistent system performance in the face of these uncertainties is the general aim of adaptive control. Improved performance is attained because the adaptive fuzzy controller can adapt to its changing surroundings. The adaptive law can assist in understanding the plant's dynamics while it is operating, and modelling is not necessary.

Manuscript received on 29 November 2023 | Revised Manuscript received on 05 December 2023 | Manuscript Accepted on 15 December 2023 | Manuscript published on 30 December 2023.

**Correspondence Author(s)*

Dr. Monisha Pathak*, Department of Instrumentation Engineering, Jorhat Engineering College, Jorhat Assam, India. E-mail: mamup@yahoo.co.in, ORCID ID: 0000-0003-3227-1991

Dr. Mrinal Buragohain, Department of Electrical Engineering, Jorhat Engineering College, Jorhat Assam, India. E-mail: mrinalburagohain@gmail.com

© The Authors. Published by Blue Eyes Intelligence Engineering and Sciences Publication (BEIESP). This is an <u>open access</u> article under the CC-BY-NC-ND license <u>http://creativecommons.org/licenses/by-nc-nd/4.0/</u>

Retrieval Number:100.1/ijeat.B43381213223 DOI: <u>10.35940/ijeat.B4338.1213223</u> Journal Website: <u>www.ijeat.org</u> To manage nonlinear systems with uncertainties, one of the strongest and most effective control strategies is sliding mode control (SMC) [8]. Attractive features include robustness to disturbances, insensitivity to matched uncertainty, and reduced-order compensated dynamics. As long as the boundaries of these disturbances are understood, it is a powerful control method that can be applied to nonlinear systems [12]. Nevertheless, sliding mode control has chattering in real-world applications and requires knowledge of the upper bound of model uncertainties as well as external disturbances [11, 14].

Therefore, adaptive fuzzy sliding mode control offers a great control solution for managing nonlinear and uncertain systems [7]. Hence, the design of adaptive fuzzy sliding mode controllers for nonlinear system control has been the subject of extensive research [13].

In this work, the design of adaptive sliding mode control utilising a fuzzy system approximation is introduced. The fuzzy system is used to approximate the unknown function of an uncertain nonlinear system. The sliding control ensures robustness, and the adaptive fuzzy system increases the system's real-time performance.

The organization of this paper is as follows: The problem formulation is introduced in Section II. The design of a fuzzy system approximation-based adaptive sliding mode controller, along with its stability analysis, is presented in Section III. In Section IV, the simulation of a second-order nonlinear system is presented to validate the given control law. A conclusion is drawn in Section V.

II. PROBLEM FORMULATION

Let us consider a second-order dynamical system as

$$\ddot{\Phi} = g(\Phi, \dot{\Phi}) + \tau + \tau_d \tag{1}$$

where Φ is the angular position, $\dot{\Phi}$ is angular speed, τ is a control input and τ_d It is a disturbance which is bounded by $|\tau_d| \leq D, D > 0$. Rewrite the above equation as

$$\dot{z}_1 = z_2$$

$$\dot{z}_2 = g(z) + \tau + \tau_d$$
(2)

where $g(z) = g(z_1, z_2) = g(\Phi, \dot{\Phi})$ It is unknown. Let us consider the desired angular position as z_d . Then the error is,

$$e = z_1 - z_d \tag{3}$$

The sliding surface is designed as $s = \dot{e} + \lambda e$ where $\lambda > 0$ Then

$$\dot{s} = \ddot{e} + \lambda \dot{e} = -\ddot{z}_d + g(z) + \tau + \lambda \dot{e} + \tau_d \tag{4}$$

Published By: Blue Eyes Intelligence Engineering and Sciences Publication (BEIESP) © Copyright: All rights reserved.



Fuzzy System Approximation based Adaptive Sliding Mode Control for Nonlinear System

Now for unknown g(z) We will approximate it using fuzzy approximation algorithms.

III. CONTROLLER DESIGN

Applying the universal approximation theorem [4] for a fuzzy system, let us design a fuzzy system $\hat{g}(z|\Phi)$ to approximate g(z).

For inputs z_1 and z_2 Define five fuzzy sets as $B_1^{l_i}$ and $B_2^{l_i}$ respectively where $l_i = 1, 2, \dots, 5$, i = 1, 2. And construct $\prod_{i=1}^{n} \rho_i = \rho_1 \times \rho_2 = 25$ Fuzzy rules. The 1st and 25th fuzzy rules are given as :

$$F^1$$
: if z_1 is B_1^1 and z_2 is B_2^1 then \hat{g} is O^1
 F^{25} : if z_1 is B_1^5 and z_2 is B_2^5 then \hat{g} is O^{25}

Where $O^{l_1 l_2}$ Is the fuzzy set of \hat{g} . Then, based on fuzzy inference, the fuzzy system's output is,

$$\hat{g}(z|\Phi_g) = \frac{\sum_{l_1=1}^5 \sum_{l_2=1}^5 x_g^{l_1 l_2} \left(\prod_{i=1}^2 \mu_{B_i^{l_i}}(z_i) \right)}{\sum_{l_1=1}^5 \sum_{l_2=1}^5 \left(\prod_{i=1}^2 \mu_{B_i^{l_i}}(z_i) \right)}$$
(5)

where $\mu_{B_i^{l_i}}(z_i)$ Is the membership function of z_i , $x_g^{l_1 l_2}$ is a free parameter and $\Phi_g = [x_g^1 \dots x_g^{25}]^T$ It is a parameter vector.

Equation (5) can be rewritten, based on the concept of fuzzy basis vector[4] as:

$$\hat{g}(z|\Phi_g) = \hat{\Phi}_g^T \psi(z) \tag{6}$$

Where $z = [z_1 \ z_2]^T$, $\psi(z)$ It is a fuzzy basis vector with $\rho_1 \times \rho_2 = 25$ elements, and its $l_1 l_2$ The element is,

$$\psi_{l_1 l_2}(z) = \frac{\prod_{i=1}^2 \mu_{B_i^{l_i}(z_i)}}{\sum_{l_{1=1}^5}^5 \sum_{l_2=1}^5 \left(\prod_{i=1}^2 \mu_{B_i^{l_i}(z_i)}\right)}$$
(7)

The membership functions can be selected based on experience and expertise.

Now, consider the optimum design parameter as

$$\Phi_g^* = \arg \min \left[\sup |\hat{g}(z|\Phi_g) - g(z)| \right]$$
(8)

Where, $z \in \mathbb{R}^2$ and $\Phi_g \in S_g$ where S_g It is a set of Φ_g .

Then,

$$g(z) = \Phi_g^{*T} \psi(z) + \varepsilon \tag{9}$$

Where is the approximation error, and $\varepsilon \leq \varepsilon_u$. Now,

$$g(z) - \hat{g}(z) = \Phi_g^{*T} \psi(z) + \varepsilon - \hat{\Phi}_g^T \psi(z) = -\tilde{\Phi}_g^T \psi(z) + \varepsilon$$
(10)

Now let us define the Lyapunov function as,

$$L = \frac{1}{2}s^2 + \frac{1}{2\theta}\widetilde{\phi}_g^T\widetilde{\phi}_g \tag{11}$$

Retrieval Number:100.1/ijeat.B43381213223 DOI: <u>10.35940/ijeat.B4338.1213223</u> Journal Website: <u>www.ijeat.org</u>

Where,
$$\theta > 0$$
 and $\tilde{\Phi}_g = \hat{\Phi}_g - \Phi_g^*$, then $\dot{\Phi}_g = \dot{\Phi}_g$
 $\dot{L} = s\dot{s} + \frac{1}{\theta}\tilde{\Phi}_g^T\dot{\Phi}_g$
 $= s(\lambda \dot{e} + g(z) + \tau - \ddot{z}_d) + \frac{1}{\theta}\tilde{\Phi}_g^T\dot{\Phi}_g$

Design control law as,

$$\tau = -\hat{g}(z) + \ddot{z}_d - \lambda \dot{e} - ksgn(s) \tag{12}$$

Choose $k \ge \varepsilon_u + D$.

Now,

$$\dot{L} = s(g(z) - \hat{g}(z) - ksgn(s)) + \frac{1}{\theta} \tilde{\Phi}_g^T \dot{\Phi}_g$$
$$\dot{L} = s(-\tilde{\Phi}_g^T \psi(z) + \varepsilon - ksgn(s)) + \frac{1}{\theta} \tilde{\Phi}_g^T \dot{\Phi}_g$$
$$\dot{L} = \varepsilon s - k|s| + \tilde{\Phi}_g^T \left(\frac{1}{\theta} \dot{\Phi}_g - s\psi(z)\right)$$

The adaptive law is chosen as,

$$\hat{\Phi}_{g} = \theta s \psi(z) \tag{13}$$

Then $\dot{L} = \varepsilon s - k|s| \le -k|s| \le 0$.

IV. SIMULATION RESULTS

Let us consider the plant of equation (1) as given below:

$$\dot{z}_1 = z_2$$
$$\dot{z}_2 = g(z) + \tau + \tau_0$$

Where $g(z) = 3(z_1 + z_2)$. Let the desired angular position be $z_d(t) = \sin(t)$. Choose five membership functions for z_i As:

$$\mu_{NM}(z_i) = \exp[-((z_i + \frac{\pi}{3}) / \frac{\pi}{12})^2]$$

$$\mu_{NS}(z_i) = \exp[-((z_i + \frac{\pi}{6}) / \frac{\pi}{12})^2]$$

$$\mu_Z(z_i) = \exp[-(z_i / \frac{\pi}{12})^2]$$

$$\mu_{PS}(z_i) = \exp[-((z_i - \frac{\pi}{6}) / \frac{\pi}{12})^2]$$

$$\mu_{PM}(z_i) = \exp[-((z_i - \frac{\pi}{3}) / \frac{\pi}{12})^2]$$

The initial states are [0.15, 0]The initial value of $\widehat{\Phi}$ Is 0.10. The controller design parameters from equations (12) and (13) are: $\lambda = 20$, $\theta = 5000$ and k = 0.55. For chattering reduction, a saturation function is used instead of the sign function with $\Delta = 0.02$.

To study the effect of disturbance, the simulation results are shown with external disturbance. τ_d Having different amplitudes. The different amplitude disturbances are : $\tau_{d1} =$ $0.5 \sin(t)$, $\tau_{d2} = \sin(t)$, and $\tau_{d3} = 5 \sin(t)$.

The results are shown in figures (1) to (15). Results includes control input, tracking of angular position and tracking of angular speed.

Published By: Blue Eyes Intelligence Engineering and Sciences Publication (BEIESP) © Copyright: All rights reserved.

31





Figures (1) to (5) show satisfactory tracking performance with negligible chattering for bounded disturbance as τ_{d1} . But for an unbounded value of disturbance, such as τ_{d2} and τ_{d3} Slight distorted tracking is observed as shown in figures (6) to (15). Figure 16 shows the membership functions.



Figure 1. Control Input for τ_{d1}



Figure 2. Tracking of Angular Position for τ_{d1}



Figure 3. Tracking of Angular Position for τ_{d1} (transient)



Figure 4. Tracking of Angular Speed τ_{d1}



Figure 5. Tracking of Angular Speed τ_{d1} (transient)

Retrieval Number:100.1/ijeat.B43381213223 DOI: <u>10.35940/ijeat.B4338.1213223</u> Journal Website: <u>www.ijeat.org</u>



Figure 6. Control Input for τ_{d2}



Figure 7. Tracking of Angular Position for au_{d2}



Figure 8. Tracking of Angular Position for τ_{d2} (transient)



Figure 9. Tracking of Angular Speed for τ_{d2}



Figure 10. Tracking of Angular Speed for τ_{d2} (transient)



Published By: Blue Eyes Intelligence Engineering and Sciences Publication (BEIESP) © Copyright: All rights reserved.



Figure 11. Control Input for τ_{d3}



Figure 12. Tracking of Angular Position for τ_{d3}



Figure 13. Tracking of Angular Position for τ_{d3} (transient)



Figure 14. Tracking of Angular Speed for τ_{d3}



Figure 15. Tracking of Angular Speed for τ_{d3} (transient)



Figure 16. Membership Functions

V. CONCLUSION

This work presents an adaptive sliding mode control utilising a fuzzy system approximation for tracking control of an uncertain nonlinear system. The fuzzy system is used to approximate the unknown function of the system. To approximate unknown nonlinearities, the fuzzy system makes use of a set of fuzzy rules, the parameters of which are continuously changed by adaptive laws. The controller ensures robust performance, and the chattering action is reduced satisfactorily. The simulation results on an uncertain nonlinear system for different amplitude disturbances validate the controller.

Funding	No, I did not receive.
Conflicts of Interest	No conflicts of interest to the best of our knowledge.
Ethical Approval and Consent to Participate	No, the article does not require ethical approval or consent to participate, as it presents evidence that is not subject to interpretation.
Availability of Data and Materials	Not relevant.
Authors Contributions	All authors have equal participation in this article.

REFERENCES

- L.X.Wang, A Course in Fuzzy Systems and Control (Prentice-Hall International, Inc., 1996).
- 2 L.X. Wang, Stable adaptive fuzzy control of nonlinear systems. IEEE Trans. Fuzzy Syst. 1(2),146-155 (1993).https://doi.org/10.1109/91.227383
- Sacheul Jeoung, Jongkil Han, Kyumann Im, Woonchul Ham, 3. Byungkook Yo, Adaptive Fuzzy Sliding Mode Control of Nonlinear System : The Second Control Scheme, Proceedings of the 1996 IEEE IECON. 22nd International Conference on Industrial Electronics, Control, and Instrumentation.
- 4. Li Xin Wang, J M Mendel, Fuzzy Basis functions, Universal Approximation, and Orthogonal Least Squares Learning, IEEE Transactions on Neural Networks, Vol3, No5 september 1992. https://doi.org/10.1109/72.159070
- 5. Tairen Sun, Yongping Pan, Adaptive Control for Nonaffine Nonlinear Systems Using Reliable Neural Network Approximation, IEEE Access. Volume 2017 https://doi.org/10.1109/ACCESS.2017.2763628
- V Nekoukar, A Erfanian, Adaptive fuzzy terminal sliding mode 6. control for a class of MIMO uncertain nonlinear systems, Fuzzy Sets 179 (2011)3449. and Systems-Elsevier. https://doi.org/10.1016/j.fss.2011.05.009
- B. Chen, X. Liu, K. Liu, C. Lin, Direct adaptive fuzzy control of nonlinear strict feedback systems, Automatica 45 (2009) 1530 - 1535 https://doi.org/10.1016/j.automatica.2009.02.021



Retrieval Number: 100.1/ijeat.B43381213223 DOI: 10.35940/ijeat.B4338.1213223 Journal Website: www.ijeat.org

Published By:



- Utkin, V.I., Guldner, J., and Shi, J. (2009).Sliding Mode Control in Electro-mechanical Systems. London, UK: Taylor /and Francis Publishers, pp. 115-130.
- J. Park, I.W. Sandberg, Universal approximation using radial basis function networks, Neural Comput. 3 (2) (1991): 246 -257. <u>https://doi.org/10.1162/neco.1991.3.2.246</u>
- Tairen Sun, Yongping Pan, Adaptive Control for Nonaffine Nonlinear Systems Using Reliable Neural Network Approximation, IEEE Access, Volume 5, 2017 https://doi.org/10.1109/ACCESS.2017.2763628
- Chuan-Kai Lin, Nonsingular Terminal Sliding Mode Control of Robot Manipulators Using Fuzzy Wavelet Networks, IEEE Transactions on Fuzzy Systems (Volume:14, Issue: 6),849 - 859,2006 https://doi.org/10.1109/TFUZZ.2006.879982
- Seul Jung, Improvement of Tracking Control of a Sliding Mode Controller for Robot Manipulators by a Neural Network, International Journal of Control, Automation and Systems 16(2) (2018) 937-943 <u>https://doi.org/10.1007/s12555-017-0186-z</u>
- Ali Saghafinia, Hew Wooi Ping, Mohammad Nasir Uddin, Khalaf Salloum Gaied, Adaptive Fuzzy Sliding-Mode Control into Chattering-Free IM Drive, IEEE Transactions on Industry Applications, 2014. <u>https://doi.org/10.1109/TIA.2014.2328711</u>
- Yuzheng Guo and Peng-YungWoo, An Adaptive Fuzzy Sliding Mode Controller for Robotic Manipulators, IEEE Transactions on Systems, Man, and Cybernetics Part A: Systems and Humans, Vol. 33, No. 2, March 2003 <u>https://doi.org/10.1109/TSMCA.2002.805804</u>

AUTHORS PROFILE



Dr. Monisha Pathak, currently an Associate Professor in the Instrumentation Engineering Department at Jorhat Engineering College, Jorhat, Assam, India, received her Bachelor of Engineering degree in Instrumentation Engineering from Jorhat Engineering College, which is affiliated with Dibrugarh University. She pursued her Master of Engineering in Power and Control from IIT

Guwahati. She completed her Ph.D. with a specialisation in Control Systems from the Department of Electrical Engineering, Dibrugarh University, Dibrugarh. Her research interests include Instrumentation and Control, Nonlinear Control, and Intelligent Control. Some of her research publications are: 1. Sliding Mode with "Adaptive Control of Robot Manipulator Trajectory Tracking using Neural Network Approximation", International Journal of Engineering and Advanced Technology (IJEAT), ISSN: 2249-8958 (Online), Volume-10 Issue-6, August 2021. 2. A New Neural Network Based Sliding Mode Adaptive Controller for Tracking Control of Robot Manipulator, International Journal of Engineering and Advanced Technology (IJEAT) ISSN: 2249-8958 (Online), Volume-11 Issue-2, December 2021, 3. "Control of nonlinear chemical process using sliding mode control", 2016 IEEE 1st International Conference on Power Electronics, Intelligent Control and Energy Systems (ICPEICES), **4-6 July 2016**



Dr. Mrinal Buragohain, currently a Professor in the Department of Electrical Engineering at Jorhat Engineering College, Jorhat, received his Bachelor of Engineering in Electrical Engineering from Assam Engineering College, affiliated with Gauhati University, Assam. He pursued his Master of Engineering in High Voltage Engineering from Kolleate. After this he completed his Ph D. with a

Jadavpur University, Koľkata. After this, he completed his Ph.D. with a specialisation in Control Systems in the Department of Electronics and Communication Engineering at the Indian Institute of Technology, Guwahati. His research interests include the application of soft computing in non-linear systems and Optimal and adaptive control. Some of his Research publications are "Tracking and Synchronization of A Hyperchaotic Hyperjerk system with No Equilibria Using Back stepping Control" at International journal for Research in Engineering Application & Management, ISSN: 2454-9150, Vol-05, Issue02, May 2019, "A PID Adaptive Sliding Mode Control for an Inverted Pendulam System for an External Disturbance using Grey Wolf Optimization Technique" at International Journal of New Technologies in Science and Engineering, ISSN: 2349-0780, Vol. 5, Issue.3, 2018

Disclaimer/Publisher's Note: The statements, opinions and data contained in all publications are solely those of the individual author(s) and contributor(s) and not of the Blue Eyes Intelligence Engineering and Sciences Publication (BEIESP)/ journal and/or the editor(s). The Blue Eyes Intelligence Engineering and Sciences Publication (BEIESP) and/or the editor(s) disclaim responsibility for any injury to people or property resulting from any ideas, methods, instructions or products referred to in the content.



Retrieval Number:100.1/ijeat.B43381213223 DOI: <u>10.35940/ijeat.B4338.1213223</u> Journal Website: <u>www.ijeat.org</u> Published By: Blue Eyes Intelligence Engineering and Sciences Publication (BEIESP) © Copyright: All rights reserved.

34